



## Grade 3 Magnetic Contacts

Full range of contacts at [www.cqr.co.uk](http://www.cqr.co.uk)


**FC508 MULTI** **FC508/WH or BR/MULTI/G3/EN**




**3** 

- Body 20(dia) x 30mm, Face Plate 22 x 33mm
- 4 Terminals
- Selectable resistors (A, B, D, E, I)
- Microswitch tamper
- Can be fitted in normal double Pole configuration
- Can be used on double doors
- Operating gap 4mm
- Magnetic immunity


**SC517 MULTI** **SC517/WH or BR/MULTI/G3/EN**




**3** 

- 65 x 13.5 x 13mm
- 4 Terminals
- Selectable resistors (A, B, D, E, I)
- Microswitch tamper
- Can be fitted in normal double Pole configuration
- Can be used on double doors
- Available white or brown
- Operating gap - 10mm
- Magnetic detection


**SC570** **SC570/WH or BR/MD/G3/EN**




**3** 

- SC570/WH or BR
- 85 x 25 x 20mm
- 6 Terminals
- Microswitch and wall tamper
- Operating gap - 10mm
- Magnetic detection


**SC570 MULTI** **SC570/WH or BR/MD/MULTI/G3**




**3** 

- 85 x 25 x 20mm
- 6 Terminals
- Selectable resistors (A, B, D, E, F, H, I)
- Microswitch and wall tamper
- Operating gap - 10mm
- Magnetic detection

**GP001** **GP001/AB/G2**



**3** 

- Heavy Duty Angled Contact
- Operating Gap: 25 mm
- Size: 85 x 27 x 26 mm
- High Quality Alloy Finish
- Pre-restored (A, B)
- 57cm Armoured Cable Lengths
- Magnetic Detection
- Other resistor value available  
- see resistor guide for type

**RS007** **RS007/G3/AB**



**3** 

- Heavy duty roller shutter
- Operating gap: 20 mm
- Size: 175 x 50 x 15 mm
- High quality alloy finish
- Selectable (A, B)
- Optional floor tamper
- Locating mechanism to aid alignment
- 45cm & 1m Armoured cable lengths
- Other resistor value available  
- see resistor guide for type

 **Independently Certified to EN50131**

**1** Grade 1 **2** Grade 2 **3** Grade 3

### Resistor Table Guide

| Type     | Resistor Guide  | Switch   | Tamper   |
|----------|---|----------|----------|
| <b>A</b> | Honeywell, Microtech (Galaxy)                                 | 1K Ohms  | 1K Ohms  |
| <b>B</b> | Scantronic, Cooper, Pyronix PCX, Texecom, Castle-Care Tec G3+ | 4K7 Ohms | 2K2 Ohms |
| <b>C</b> | Guardall (Network 1 configuration) Two wire only              | 8K2 Ohms | 8K2 Ohms |
| <b>D</b> | DSC   | 5K6 Ohms | 5K6 Ohms |
| <b>E</b> | Gardtec   | 6K8 Ohms | 4K7 Ohms |

| Type     | Resistor Guide                    | Switch   | Tamper   |
|----------|-----------------------------------|----------|----------|
| <b>F</b> | Bosch, DA Abacus                  | 8K2 Ohms | 3K9 Ohms |
| <b>G</b> | Castle Care-Tec                   | 13K Ohms | 1K Ohms  |
| <b>H</b> | Europlex, MDT                     | 2K2 Ohms | 2K2 Ohms |
| <b>I</b> | Pyronix Matrix, GE / Aritech, HKC | 4K7 Ohms | 4K7 Ohms |
| <b>J</b> | Texecom                           | 22K Ohms | 10K Ohms |